



TP70/P5 Protocol for ICT002 / Pulse

USD6 Support bill 1、5、10、20、50、100 (America)

DIP SW SETTING : 1

FUNCTION		SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / USD 1	OFF	OFF	OFF							
	2 Pulse / USD 1	OFF	OFF	ON							
	3 Pulse / USD 1	OFF	ON	OFF							
	4 Pulse / USD 1	OFF	ON	ON							
	5 Pulse / USD 1	ON	OFF	OFF							
	10 Pulse / USD 1	ON	OFF	ON							
	20 Pulse / USD 1	ON	ON	OFF							
	100 Pulse / USD 1	ON	ON	ON							
	Fast Output Pulse	Lo=50ms Hi=100ms			ON						
★	Slow Output Pulse	Lo=50ms Hi=300ms			OFF						
	Inhibit level Active Low				ON						
★	Inhibit level Active High				OFF						
★	Accept USD 1						ON				
	Reject USD 1						OFF				
★	Accept USD 5						ON				
	Reject USD 5						OFF				
★	Accept USD 10						ON				
	Reject USD 10						OFF				
★	Accept USD 20						ON				
	Reject USD 20						OFF				
★	Accept USD 50 & 100						ON				
	Reject USD 50 & 100						OFF				

★ Manufacture setting

Note: (1) Please reset the bill acceptor after any changes on Dip switch.

(2) Dip Switch 1 to 5 are only for Pulse mode.

DIP SW SETTING : 2

FUNCTION		SW1	SW2	SW3	SW4
★	Pulse Normal High (NO)	ON			
	Pulse Normal Low (NC)	OFF			
★	Pulse Protocol		ON		
	ICT Protocol		OFF		
	Straight			ON	
★	Turn Over			OFF	
	Ignore Sensor Problem (Note 1)				ON
★	Acknowledge Sensor Problem (Note 2)				OFF

★ Manufacture setting

Note: (1) Sensor 6 problem occurred ==>> BA will be still in working order.

(The face LED will be Flashing in short green about 2 seconds everytime you restart BA.)

(2) BA will stop to work when it acknowledges Sensor 6 problem occurred.