



TP83P3B Protocol for RS232 004 / Pulse

XAF5 Support bill 500、1000、2000、5000、10000 (CentralAfrican)

DIP SW SETTING : 1

FUNCTION		SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / XAF 500	OFF	OFF	OFF							
	2 Pulse / XAF 500	OFF	OFF	ON							
	3 Pulse / XAF 500	OFF	ON	OFF							
	4 Pulse / XAF 500	OFF	ON	ON							
	5 Pulse / XAF 500	ON	OFF	OFF							
	10 Pulse / XAF 500	ON	OFF	ON							
	20 Pulse / XAF 500	ON	ON	OFF							
	100 Pulse / XAF 500	ON	ON	ON							
	Fast Output Pulse	Lo=50ms Hi=100ms			ON						
★	Slow Output Pulse	Lo=50ms Hi=300ms			OFF						
	Inhibit level Active Low					ON					
★	Inhibit level Active High					OFF					
★	Accept XAF 500						ON				
	Reject XAF 500						OFF				
★	Accept XAF 1000							ON			
	Reject XAF 1000							OFF			
★	Accept XAF 2000								ON		
	Reject XAF 2000								OFF		
★	Accept XAF 5000									ON	
	Reject XAF 5000									OFF	
★	Accept XAF 10000										ON
	Reject XAF 10000										OFF

★ Default setting

Note: Please reset the bill acceptor after any changes on Dip switch.

DIP SW SETTING : 2

FUNCTION		SW1	SW2	SW3	SW4
★	Pulse Normal High (NO)	ON			
	Pulse Normal Low (NC)	OFF			
★	Pulse Protocol		ON		
	RS232 Protocol		OFF		
	Straight			ON	
★	Turn Over			OFF	
	Reserved				ON
★	Reserved				OFF

★ Default setting

Note: Please reset the bill acceptor after any changes on Dip switch