



# TP83P3B Protocol for RS232 004 / Pulse

NGN8 Support bill 5、10、20、50、100、200、500、1000 (Nigeria)

## DIP SW SETTING : 1

FUNCTION		SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / NGN 5	OFF	OFF	OFF							
	2 Pulse / NGN 5	OFF	OFF	ON							
	3 Pulse / NGN 5	OFF	ON	OFF							
	4 Pulse / NGN 5	OFF	ON	ON							
	5 Pulse / NGN 5	ON	OFF	OFF							
	10 Pulse / NGN 5	ON	OFF	ON							
	20 Pulse / NGN 5	ON	ON	OFF							
	100 Pulse / NGN 5	ON	ON	ON							
	Fast Output Pulse	Lo=50ms Hi=100ms			ON						
★	Slow Output Pulse	Lo=50ms Hi=300ms			OFF						
	Inhibit level Active Low					ON					
★	Inhibit level Active High					OFF					
★	Accept NGN 5						ON				
	Reject NGN 5						OFF				
★	Accept NGN 10							ON			
	Reject NGN 10							OFF			
★	Accept NGN 20 & 50								ON		
	Reject NGN 20 & 50								OFF		
★	Accept NGN 100 & 200									ON	
	Reject NGN 100 & 200									OFF	
★	Accept NGN 500 & 1000										ON
	Reject NGN 500 & 1000										OFF

★ Default setting

Note: Please reset the bill acceptor after any changes on Dip switch.

## DIP SW SETTING : 2

FUNCTION		SW1	SW2	SW3	SW4
★	Pulse Normal High (NO)	ON			
	Pulse Normal Low (NC)	OFF			
★	Pulse Protocol		ON		
	RS232 Protocol		OFF		
	Straight			ON	
★	Turn Over			OFF	
	Reserved				ON
★	Reserved				OFF

★ Default setting

Note: Please reset the bill acceptor after any changes on Dip switch