



# TP70P3B/P5 Protocol for RS232 104U / Pulse

NPR7 Support bill 5、10、20、50、100、500、1000 (Nepal)

## DIP SW SETTING : 1

FUNCTION		SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / NPR 5	OFF	OFF	OFF							
	2 Pulse / NPR 5	OFF	OFF	ON							
	3 Pulse / NPR 5	OFF	ON	OFF							
	4 Pulse / NPR 5	OFF	ON	ON							
	5 Pulse / NPR 5	ON	OFF	OFF							
	10 Pulse / NPR 5	ON	OFF	ON							
	20 Pulse / NPR 5	ON	ON	OFF							
	100 Pulse / NPR 5	ON	ON	ON							
	Fast Output Pulse	Lo=50ms Hi=100ms			ON						
★	Slow Output Pulse	Lo=50ms Hi=300ms			OFF						
	Inhibit level Active Low				ON						
★	Inhibit level Active High				OFF						
★	Accept PHP 5 & 10				ON						
	Reject PHP 5 & 10				OFF						
★	Accept PHP 20				ON						
	Reject PHP 20				OFF						
★	Accept PHP 50				ON						
	Reject PHP 50				OFF						
★	Accept PHP 100				ON						
	Reject PHP 100				OFF						
★	Accept PHP 500 & 1000				ON						
	Reject PHP 500 & 1000				OFF						

★ Default setting

Note: Please reset the bill acceptor after any changes on Dip switch.

## DIP SW SETTING : 2

FUNCTION		SW1	SW2	SW3	SW4
★	Pulse Normal High (NO)	ON			
	Pulse Normal Low (NC)	OFF			
★	Pulse Protocol		ON		
	RS232 Protocol		OFF		
	Straight			ON	
★	Turn Over			OFF	
	Reserved				ON
★	Reserved				OFF

★ Default setting

Note: Please reset the bill acceptor after any changes on Dip switch.