



TP70P3B/P5 Protocol for RS232 004 / Pulse

SAR4 Support bill 1 、 5 、 10 、 50 (Saudi_Arabia)

DIP SW SETTING : 1

FUNCTION		SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / SAR 1	OFF	OFF	OFF							
	2 Pulse / SAR 1	OFF	OFF	ON							
	3 Pulse / SAR 1	OFF	ON	OFF							
	4 Pulse / SAR 1	OFF	ON	ON							
	5 Pulse / SAR 1	ON	OFF	OFF							
	10 Pulse / SAR 1	ON	OFF	ON							
	20 Pulse / SAR 1	ON	ON	OFF							
	100 Pulse / SAR 1	ON	ON	ON							
	Fast Output Pulse	Lo=50ms Hi=100ms			ON						
★	Slow Output Pulse	Lo=50ms Hi=300ms			OFF						
	Inhibit level Active Low					ON					
★	Inhibit level Active High					OFF					
★	Accept SAR 1						ON				
	Reject SAR 1						OFF				
★	Accept SAR 5							ON			
	Reject SAR 5							OFF			
★	Accept SAR 10								ON		
	Reject SAR 10								OFF		
★	Accept SAR 50									ON	
	Reject SAR 50									OFF	
★	Reserved										ON
	Reserved										OFF

★ Default setting

Note: Please reset the bill acceptor after any changes on Dip switch.

DIP SW SETTING : 2

FUNCTION	SW1	SW2	SW3	SW4
★ Pulse Normal High (NO)	ON			
Pulse Normal Low (NC)	OFF			
★ Pulse Protocol		ON		
RS232 Protocol		OFF		
Straight			ON	
★ Turn Over			OFF	
Special Pulse				ON
★ Normal Pulse				OFF

Special Pulse	
Currency	Pulse
SAR 10	5
SAR 20	10
SAR 30	15
SAR 40	20
SAR 50	30

★ Default setting

Note: Please reset the bill acceptor after any changes on Dip switch