



TP70/P5 Protocol for ICT002 / Pulse

BRC6 Support bill 2, 5, 10, 20, 50, 100 (Brazil)

DIP SW SETTING : 1

FUNCTION			SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / BRC 1		OFF	OFF								
	2 Pulse / BRC 1		OFF	ON								
	4 Pulse / BRC 1		ON	OFF								
	10 Pulse / BRC 1		ON	ON								
		Note1	Note2									
★	Output Pulse	Lo=50ms Hi=100ms		Lo=20ms Hi=50ms	OFF	OFF						
	Output Pulse	Lo=150ms Hi=100ms		Lo=15ms Hi=20ms	OFF	ON						
	Output Pulse	Lo=20ms Hi=100ms		Lo=15ms Hi=30ms	ON	OFF						
	Output Pulse	Lo=30ms Hi=150ms		Lo=30ms Hi=30ms	ON	ON						
	Inhibit level Active Low							ON				
★	Inhibit level Active High							OFF				
★	Accept BRC 2							ON				
	Reject BRC 2							OFF				
★	Accept BRC 5								ON			
	Reject BRC 5								OFF			
★	Accept BRC 10 & 20									ON		
	Reject BRC 10 & 20									OFF		
★	Accept BRC 50										ON	
	Reject BRC 50										OFF	
★	Accept BRC 100											ON
	Reject BRC 100											OFF

★ Manufacture setting

Note: (1) Please reset the bill acceptor after any changes on Dip switch.

(2) Dip Switch 1 to 5 are only for Pulse mode.

DIP SW SETTING : 2

FUNCTION	SW1	SW2	SW3	SW4
★ Pulse Normal High (NO)	ON			
Pulse Normal Low (NC)	OFF			
★ Pulse Protocol		ON		
ICT Protocol		OFF		
Straight			ON	
★ Turn Over			OFF	
Refer to Note 2				ON
★ Refer to Note 1				OFF

Note 1	
Currency	Pulse
BRC 2	2
BRC 5	5
BRC 10	10
BRC 20	20
BRC 50	50
BRC 100	100

Note 2	
Currency	Pulse
BRC 2	2
BRC 5	3
BRC 10	4
BRC 20	5
BRC 50	6
BRC 100	7

★ Manufacture setting

Note: (1) Please reset the bill acceptor after any changes on Dip switch

(2) High acceptance mode will increasing accepting rate, however, it will reduce the security level of Bill Acceptor.