



TP70/P5 Protocol for ICT004 / Pulse

TZS5 Support bill 500, 1000, 2000, 5000, 10000 (Tanzanian)

DIP SW SETTING : 1

FUNCTION		SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / TZS 500	OFF	OFF	OFF							
	2 Pulse / TZS 500	OFF	OFF	ON							
	3 Pulse / TZS 500	OFF	ON	OFF							
	4 Pulse / TZS 500	OFF	ON	ON							
	5 Pulse / TZS 500	ON	OFF	OFF							
	10 Pulse / TZS 500	ON	OFF	ON							
	20 Pulse / TZS 500	ON	ON	OFF							
	100 Pulse / TZS 500	ON	ON	ON							
	Fast Output Pulse	Lo=50ms Hi=100ms			ON						
★	Slow Output Pulse	Lo=50ms Hi=300ms			OFF						
	Inhibit level Active Low					ON					
★	Inhibit level Active High					OFF					
★	Accept TZS 500						ON				
	Reject TZS 500						OFF				
★	Accept TZS 1000							ON			
	Reject TZS 1000							OFF			
★	Accept TZS 2000								ON		
	Reject TZS 2000								OFF		
★	Accept TZS 5000									ON	
	Reject TZS 5000									OFF	
★	Accept TZS 10000										ON
	Reject TZS 10000										OFF

★ Manufacture setting

Note: (1) Please reset the bill acceptor after any changes on Dip switch.

(2) Dip Switch 1 to 5 are only for Pulse mode.

DIP SW SETTING : 2

FUNCTION	SW1	SW2	SW3	SW4
★ Pulse Normal High (NO)	ON			
Pulse Normal Low (NC)	OFF			
★ Pulse Protocol		ON		
ICT Protocol		OFF		
Straight			ON	
★ Turn Over			OFF	
Reserved				ON
★ Reserved				OFF

★ Manufacture setting

Note: (1) Please reset the bill acceptor after any changes on Dip switch