



TP77 Protocol for ICT104 / Pulse

INR7 Support bill 5, 10, 20, 50, 100, 500, 1000 (India)

DIP SW SETTING : 1

FUNCTION		SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / INR 5	OFF	OFF	OFF							
	2 Pulse / INR 5	OFF	OFF	ON							
	3 Pulse / INR 5	OFF	ON	OFF							
	4 Pulse / INR 5	OFF	ON	ON							
	5 Pulse / INR 5	ON	OFF	OFF							
	10 Pulse / INR 5	ON	OFF	ON							
	20 Pulse / INR 5	ON	ON	OFF							
	100 Pulse / INR 5	ON	ON	ON							
	Fast Output Pulse	Lo=50ms Hi=100ms			ON						
★	Slow Output Pulse	Lo=50ms Hi=300ms			OFF						
	Inhibit level Active Low				ON						
★	Inhibit level Active High				OFF						
★	Accept INR 5 & 10 & 20				ON						
	Reject INR 5 & 10 & 20				OFF						
★	Accept INR 50				ON						
	Reject INR 50				OFF						
★	Accept INR 100				ON						
	Reject INR 100				OFF						
★	Accept INR 500				ON						
	Reject INR 500				OFF						
★	Accept INR 1000 (CashBox Reject)				ON						
	Reject INR 1000 (CashBox Reject)				OFF						

★ Manufacture setting

Note: (1) Please reset the bill acceptor after any changes on Dip switch.

(2) Dip Switch 1 to 5 are only for Pulse mode.

DIP SW SETTING : 2

FUNCTION	SW1	SW2	SW3	SW4
★ Pulse Normal High (NO)	ON			
Pulse Normal Low (NC)	OFF			
★ Pulse Protocol		ON		
ICT Protocol		OFF		
Straight			ON	
★ Turn Over			OFF	
Manufacture Default				ON
★ System Default				OFF

★ Manufacture setting

Note: (1) Please reset the bill acceptor after any changes on Dip switch

(2) Dip Switches 1 & 3 are only used for pulse protocol.